



.....	1
ComilDE .....	1
ini .....	3

× StandAlone EtherCAT



- ComiIDE , Setup



- EtherCAT IP

Setup

Basic

Platform

Form

HotKey

Device

EtherCAT

EtherCAT IP

OK Cancel

**Mode**

StandAlone EtherCAT 사용

Simulation Mode 사용

DC Delay 4000

**Control Message Setup**

Local IP 192,168,1,49

Daemon IP 192,168,1,49

Daemon Port L 55000

Daemon Port M 5000

RX TimeOut L 3000

RX TimeOut M 2000

Comm Retry Count 0

**IO Message Setup**

Master IP 192,168,1,100

InPort 35040


OutPort 35041

• StandAlone EtherCAT

- , PCI Type EtherCAT Master .


• Local IP, Daemon IP

- Local IP Daemon IP PC IP .



- Master IP
  - Master IP StandAlone EtherCAT Master IP
  - 192.168.1.100

ini



- ..\AppData\Roaming\COMIZOA\ComiEcatLibCfg.ini
  - %appdata%\comizoa

```
1
2 [DEBUG LOGGING]
3   LogType=3
4   LogLevel=2
5   LogFilePath=D:\10_Project\ComiIDE\ComiIDE\bin\Debug\Logs\log_200827_160
6   ErrLogType=0
7   Exclude=
8   Include=
9 [MEMORY LOG OPTIONS]
10  MemorySize (KB)=400000
11
12 [LIB_TUNES]
13  DC Setup Delay=4000
14  EmbeddedMode=1
15  SimulationMode=0
16
17 [CONTROL MSG COMM]
18  LOCAL_IP =192.168.1.49
19  DAEMON_IP =192.168.1.49
20  DAEMON_PORT_L =55000
21  DAEMON_PORT_M =5000
22  RX_TIMEOUT_L =3000
23  RX_TIMEOUT_M =2000
24  COMM_RETRY_NUM =0
25
26 [LIO_MSG_COMM]
27  MASTER_IP =192.168.1.100
28  IN_PORT =35040
29  OUT_PORT =35041
30
```

- 'EmbeddedMode' 1 .
- 'Local\_IP', 'Daemon\_IP' PC IP .
- 'Master\_IP' , 'Master\_IP' .

From:

<http://comizoa.co.kr/info/> - -

Permanent link:

[http://comizoa.co.kr/info/doku.php?id=platform:ethercat:1\\_setup:20\\_ip:10\\_begin](http://comizoa.co.kr/info/doku.php?id=platform:ethercat:1_setup:20_ip:10_begin)

Last update: **2024/07/08 18:23**